

AAP 8000E3



Frequency	Hz	50
Model	AAP 8000E3	

SPECIFICATIONS



Fuel gauge

Fuel gauge is on the fuel tank



OHV

Over Head Valve easy to maintenance



Oil level alarm

When the oil level is low that the engine will not start.



AVR

AVR is a device often solid state, for controlling the output voltage of a generator.



Maintenance free battery

It is long life



Wheel kit

Easy Transportation



Circuit Protector

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.



Generator set out put sockets



Voltmeter

It is a gauge for out put voltage of generator set.



Choke System

When the cold weather, choke system aid to operate the engine



Dual Element air filter



Large capacity fuel tank

15-25 L

AAP 8000E3

GENERATING SET

AC Rated Power	kW	6,00
	kVA	7,50
Maximum Power	kW	6,50
	kVA	8,00
AC Rated Current	AC Rated Current	11,00
DC Rated Current	AC Rated Current	8,00
Voltage	V	400
Frequency	Hz	50
Phase		3
Power Factor		1,00
Fuel Consumption	L/h.	2,50
Run Time	Hour	8,00
Noise Level	dB(A)	76,00

ENGINE

Speed	rpm	3000
Power	Hp	15,0
Cylinder No.		1,0
Cylinder Bulk	mL.	419
Fuel Type		Gasoline
Oil Capacity	L	1,1
Fuel Tank Capacity	L	30,0
Start Type		Electrical

DIMENSIONS

Width	mm.	810
Lenght	mm.	540
Height	mm.	575
Dry Weight	kg.	98,0