

AAP 1200

ACTIVE POWER



Frequency	Hz	50
Model		AAP 1200

SPECIFICATIONS



Fuel gauge

Fuel gauge is on the fuel tank



OHV

Over Head Valve easy to maintenance



Oil level alarm

When the oil level is low that the engine will not start.



AVR

AVR is a device often solid state, for controlling the output voltage of a generator.



Circuit Protector

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.



Voltmeter

It is a gauge for out put voltage of generator set.



Choke System

When the cold weather, choke system aid to operate the engine



Dual Element air filter

AAP 1200



GENERATING SET

AC Rated Power	kW	0,90
Maximum Power	kW	1,00
AC Rated Current	AC Rated Current	3,40
Voltage	V	230
Frequency	Hz	50
Phase		1
Power Factor		1,00
Fuel Consumption	L/h.	0,50
Noise Level	dB(A)	66,00

ENGINE

Speed	rpm	3000
Fuel Type		Gasoline
Oil Capacity	L	0,4
Fuel Tank Capacity	L	7,0
Start Type		Rope

DIMENSIONS

Width	mm.	355
Lenght	mm.	465
Height	mm.	385
Dry Weight	kg.	26,0