

Remote Control Panel FS5200R



The function of the Repeater is to receive and transmit data from remote Fire Control Panels.

Repeater FS5200R is a unit supplementing the range of 5000 series products expanding the possibilities of the fire detecting and fire extinguishing systems built on the basis of fire control panels FS5100, FS5200, FS5200E and FS4000. EN54-4 compatible built-in Power Supply Unit. EN54-2 compatible fire alarm lines and fault warning output.

**MORE THAN 10 DISPLAY
LANGUAGES AVAILABLE**

Features

Some of the main FS5200R features and possibilities are:

- Indicates Fire condition and/or Fault condition occurred in each of the fire control panels connected to it
- Control effect on the connected fire control panels that have sent a signal for Fire condition
- User oriented menu dialogue for easy and convenient operation
- Four-line LCD for visualization the different modes of the repeater
- LEDs and sound indication of the operation modes
- User oriented test modes allowing for a total control of the site protected

Functional characteristics:

- Connection of maximum 15 remote fire control panels (repeaters) to one repeater
- Built-in buzzer for fire condition – one tonal, discontinuous, can be switched off
- Built-in buzzer for fault condition – one tonal, discontinuous, can be switched off
- Built-in real time clock
- Interfaces for communication with the fire control panels RS485 connected to it
- Option to prolong the time period for fire condition stage I with programmable inspection period
- Possibility for delay when switching the outputs for Fire alarm
- Energy independent archive – up to 100 events
- Operation with a wide range of output devices

Technical data

Maximum number of remote fire control panels: 15 pcs

Monitored fire alarm lines (EN 54-2, class C) 2 pcs:
– Type: potential
– Electrical characteristics: (24±3)V DC / 1A

Common fire relay output: 1 pc
– Type: potential free, switching
– Electrical characteristics: 3A/125V AC;
3A/30V DC

Common fault warning relay output: 1 pc
– Type: potential free, switching
– Electrical characteristics: 3A/125V DC;
3A/30V DC

Indications of registered events:

- Light indication: LED
- Text messages: LCD display, 4 lines 20 characters per line, Cyrillic letters
- Sound signaling: built-in buzzer

Maximum current to external devices:
– 1,2A at (24±3)V DC

Power supply:
Mains: 220/230V AC, 50Hz

Backup batteries:
– Batteries type: lead, gel electrolyte
– Number of batteries: 2 pcs
– Connection: consecutive
– Nominal capacity C20: (1,2-4,5) Ah

Operating temperature: minus 5 °C to 40 °C
Relative humidity: (92±3)% at 40 °C
Dimensions: 313 x 218 x 85 mm
Weight: 1,6 kg



Office building UniPOS,
1 Efr. Nikola Paskalev Str., Mladost 1, Sofia 1748, Bulgaria
Phone: +359 2 97 439 25, +359 2 97 444 69

47 San Stefano Str., Pleven 5800, Bulgaria
Phone: +359 64 891 100

www.unipos-bg.com

www.famcocorp.com

E-mail: info@famcocorp.com

@famco_group

Tel: +۳۱- ۴ ۸ ۰ ۰ ۰ ۰ ۴ ۹

Fax : +۳۱ - ۴ ۴ ۹ ۹ ۴ ۶ ۴ ۲

تهران، کیلومتر ۲۱ بزرگراه لشگری (جاده مخصوص کرج)

روبروی پالایشگاه نفت پارس، پلاک ۱۲