



AC-11/AC-15/AC-15EX /AC-16 Series

Non-Contact AC Voltage Detectors

The Non-contact AC Voltage Testers are easy to use — just touch the tip to a terminal strip, outlet, or supply cord. When the tip glows red and the unit beeps, you know there's voltage present. Electricians, maintenance, service, safety personnel, and homeowners can quickly test for energized circuits in the workplace or at home.



Features:

- I High power rear flashlight
- I Thinner probe tip for working with wall outlets
- I Green LED means power on, flashing red LED with beeper means voltage detected
- I Low battery selftest & Auto power off
- I Two modes, green means high voltage mode, yellow means low voltage mode
- I Forward facing flashlight
- I Flash and Beep rate increase as the detector gets closer to the voltage source helping the user pinpoint live circuits
- I Power ON/OFF swith & Silent Mode
- I Pocket clip for easy storage
- I CATIV-1000V , IP67 Water proof & 2m drop-proof
- I ATEX certificate for AC-15Ex/AC-15Exs

Specifications												
		AC-1 1	AC-1 1B	AC-1 1S	AC-1 5	AC-1 5B	AC-1 5S	AC-15 Ex	AC-1 5 Exs	AC-1 6	AC-1 6B	AC-1 6S
ACV Non-Contact Detection		*	*	*	*	*	*	*	*	*	*	*
Operating Range(50Hz/60 Hz)	12V to 1000V	*			*			*		*		
	24V to 1000V		*			*					*	
	50V to 1000V			*			*		*			*
	100V to 1000V	*	*		*	*		*		*	*	
	200V to 1000V			*			*		*			*
IP67 Water proof & 2m drop-proof		2m drop-proof			*	*	*	*	*	*	*	*
Motor Shaking				*			*		*			*
Ex ib IIB T4 (ATEX)								*	*			
Dual Voltage Sensitivity detector												
Red/Yellow/Green LED indicators												
Flashlight function												
Auto Power Off												
Beeper sounds												
System self test												
Switchable audible and silent mode												
Rugged, double molded case												
CATIV-1000V												
Size(HxWxD)		160 x 20 x 23			160mm x 23mm x 25mm			155mm x 20mm x 22mm				
Weight		60g			55g			48g				

Accessories: Two "AAA" batteries and clamshell.